

Cinelex SKYBRIDGE

Wi-Fi Art-Net To Wireless DMX Converter

MULTI-PROTOCOL

SKYBRIDGE combines Art-Net & LumenRadio into a single device.

REAL-TIME TRANSLATION

Dynamic protocol translation in real-time, with no delay.

COMPLEX, SIMPLIFIED

Control elaborate lighting rigs. Use any Art-Net control device with any LumenRadio light fixture or receiver.

WIRED & WIRELESS

LumenRadio transmitter & DMX XLR connector ensures seamless integration into any workflow setup.

USB-POWERED

Power SKYBRIDGE from any 5V USB source.



Wireless Protocol

Protocol	Art-Net / LumenRadio
Operational Frequency	5GHz (Wi-Fi) / 2.4GHz (LumenRadio)
Range	30m (Wi-Fi) / 100m (LumenRadio)

Power

USB Type-B	5V
Power Consumption	1.8W

Controls

1x "SYNC" Button	Synchronise SKYBRIDGE with DMX Receivers/Lights
------------------	---

Connectors

1x DMX XLR 5-Pin Female	
1x USB Type-B Power Input Female	
1x Antennae	

LED Indicators

1x "POWER" LED	Power Input Confirmation
1x "ART-NET" LED	Art-Net Packet Activity Status
1x "STATUS" LED	DMX Connection Status

Size (without Antennae)

Weight	295g
Dimensions	145mm x 140mm x 41mm (L x W x D)